

PARTITORI CON CONNETTORI F

RI 2 • RF 12 • RF 13 • RF 14
RF 16 • RF 18

Ltè2

- ✓ Efficienza di schermatura classe A
- ✓ Passaggio DC su tutte le uscite
- ✓ 5-2400 MHz
- ✓ Protezione da esterno (opzionale)



RI 2



PMM



RF 12



RF 13 • RF 14



RF 16 • RF 18



TABELLA TECNICA

ARTICOLO		RI 2	RF 12	RF 13	RF 14	RF 16	RF 18
Codice		141006	141001	141002	141003	141004	141005
Banda passante	MHz	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400
Uscite	N°	2	2	3	4	6	8
Perdite di passaggio	dB 860 MHz dB 2400 MHz	4 5,5	4 5,5	7 9,5	8,1 10	11 14,5	12 15,5
Isolamento tra uscite	dB	>20	>20	>20	>20	>20	>20
Perdite di ritorno	dB	>10	>10	>10	>10	>10	>10
Passaggio DC	mA	800	800	800	800	800	800

ARTICOLO		PMM
Codice		024001