

AMPLIFICADORES MONOCANAL SERIE ASU*

**AS FM · AS DAB · AS UXX* ·
AS FI · PM · FA 2412 · CH 4 ·
CH 10 · IEC 75 · MAM**



PM



CH 10



FA 2412

*Indicar canal

TABLA TÉCNICA

REFERENCIA		AS UXX*	AS FM	AS DAB	AS FI
Código		220001	220016	220010	220018
Banda cubierta		1 canal UHF	FM	DAB	FI
Ganancia	dB	45	20	45	35
Figura de ruido	dB	8	8	8	8
Nivel de salida DIN 45004K	dB μ V	120	-	-	-
Nivel de salida EN 50083-3, -35 dB	dB μ V	113	90	120	120
Pérdidas de retorno salida	dB	>6	>6	>6	>6
Alimentación	Vcc	24	24	24	24
Consumo	mA	100	80	100	100

*Indicar canal

ACCESORIOS

REFERENCIA	CÓDIGO	DESCRIPCIÓN
PM	220004	Puente de mezcla
FA 2412	220014	Alimentador modular 24V/1,2A
CH 4	220008	Chasis 4 unidades
CH 10	220013	Chasis 10 unidades
IEC 75	220012	Carga 75 Ω IEC
MAM	220025	Montaje y ajuste de equipos monocanales completos