

**Ek**

EKSELANS BY ITS

# MAST AMPLIFIER + POWER SUPPLY KIT

## KIT AM 311

AM 311 L2  
+ FA 24 S

### AM 311

- ✓ Excellent gain / output level ratio
- ✓ Low noise factor
- ✓ ABS plastic case, IP 23, with self-supporting lid and closure for coaxial cables
- ✓ Swivel amplifier for easy connection.
- ✓ DC current pass at UHF input

### FA 24 S

- ✓ Ultra-compact size
- ✓ High efficiency
- ✓ Operation indicator LED
- ✓ Discrete for domestic purpose

**AM 311 L2****FA 24 S****MAST AMPLIFICATION KIT  
IN SINGLE BOX**



## TECHNICAL TABLE

REFERENCIA		KIT AM 311
Código		051038

  

REFERENCE		AM 311 L2
Code		051024
Inputs		UHF
Frequency range	MHz	470-694
Gain	dB	35
Regulation	dB	15
Output level (DIN 45004B)	dB $\mu$ V	110
Noise factor	dB	<2
Mains voltage	Vdc	24
DC Pass		√
Current consumption	mA	≤ 70
Second output / test	dB	-

  

REFERENCE		FA 24 S
Code		052003
Salidas	Nº	2
Frecuencias	MHz	47-862
Pérdidas de paso	dB	<4
Tensión de salida	Vdc	24
Corriente máxima	mA	150
Alimentación	Vac	100/240
Dimensiones	mm	86 x 65 x 23