

MID-POWER BROADBAND MICRO AMPLIFIER

MCA 402 L2

Lte2

- √ Suitable for amplifying terrestrial signals in small and medium buildings
- √ Ultra compact size
- √ Independent gain control for each input
- √ Remote powering voltage for pre-amplifiers (AL 23)
- √ High efficiency power supply



MCA 402 L2

TECHNICAL INFORMATION

REFERENCE		MCA 402 L2	
Code		061008	
Inputs		VHF	UHF
Frequency range	MHz	47-230	470-694
Gain	dB	32	40
Regulation	dB	17	16
Output level (DIN 45004B)	dBμV	117	114
Return loss	dB	>15	
Noise factor	dB	<4	
Mains voltage	Vac	230 ±10%	
Switchable 12V current pass	mA	-	100
Consumption	W	2,2	