

ICT DIPLEXER

MI 3 ICT

- ✓ Low insertion loss
- ✓ SAT inputs with DC pass



MI 3 ICT

TECHNICAL TABLE

| REFERENCE | | MI 3 ICT | | |
|-----------------|-----|------------------------------|----------|----------|
| Inputs | | TER | SAT1 | SAT 2 |
| Frequency Range | MHz | 5-862 | 950-2400 | 950-2400 |
| Insertion loss | dB | 4 | 2 | 2 |
| Rejection | dB | 30 | 25 | 25 |
| DC Pass | mA | - | 500 | 500 |
| Outputs | N° | 2= TER + SAT 1 / TER + SAT 2 | | |