

**MEZCLADOR MI 3 ICT
COUPLEUR MI 3 ICT
MISCELLATORE MI 3 ICT
MISTURADOR MI 3 ICT
DIPLEXER MI 3 ICT**

REFERENCIA	RÉFÉRENCE	ARTICOLO	REFERÊNCIA	REFERENCE		MI 3 ICT		
Entradas	Entrées	Ingressi	Entradas	Inputs		TER	SAT 1	SAT 2
Frecuencias	Bande passante	Frequenze	Frequências	Frequency Range	MHz	5-862	950-2300	950-2300
Pérdidas de paso	Affaiblissement de passage	Perdite di passaggio	Perdas inserção	Insertion loss	dB	4	2	2
Rechazo	Réjection	Separazione	Rejeição	Rejection	dB	30	25	25
Paso de corriente	Passage de courant	Passaggio DC	Passagem de corrente	DC Pass	mA	-	500	500
Salidas	Sorties	Uscite	Sáidas	Outputs	Nº	2= TER + SAT 1 / TER + SAT 2		



Montaje conector F Assemblage de connecteur F Montaggio connettore F Montagem de conector F F connector assembly

