

PROGRAMMABLE AMPLIFIERS AP 8

- Fully-automatic programming system at the press of a button
- Intelligently performed configuration which fits best at every installation
- 8 programmable UHF filters
- Up to 7 channels per filter (56 MHz)
- Selectable option to cancel LTE band

REFERENCE	AP EASY			
Code	071007			
Inputs		BI/FM	BIII/ DAB	UHF
Frequency Range	MHz	47-108	174-230	470-790* / 862
Return loss	dB	>10	>10	>10
Gain	dB	27	25	50/35*
Regulation	dB	20	20	20
Maximum input level	dB	90	80	45/95
Output level DIN 45004B	dBµV	114	114	116
Noise figure	dB	9	4	7
Selectivity (+ / -16 MHz)	dB	-	-	>16
Mains voltage	Vac	230 +/-10%		
	Vdc	12/400 mA		

*790 MHz with LTE ON



INCLUDED

PR AP programmer

Enables the possibility of modifying the parameters automatically selected by the amplifier

CODE	REFERENCE	DESCRIPTION
072002	PR AP	AP Easy programmer

