

INDOOR AMPLIFIER

QuiCoax®

AA QC 211 · AA QC 182

THE PERFECT
TECHNICAL
SOLUTION
FOR ANY
INSTALLATION

- ✓ Ultra Compact Size
- ✓ Suitable for 80x80mm junction box
- ✓ Easy to install, just a few seconds
- ✓ Quicoax connection system
- ✓ Zamak quicoax case high protection
- ✓ Working led indicator
- ✓ New generation quicoax system, even easier connection
- ✓ Its very high saturation level allows simultaneous treatment of weak signals with other very powerful without intermodulating



AA QC 211



Suitable for 80x80mm junction box

01



Reduce to
minimum
**installation
time**

02



No need
of **tools**

03



Guarantees
an **excellent
connected** and
minimizes the
space

04



Very high
**shielding
factor CLASS A**
throughout the
band

05



Eliminate the
use of **connec-
tors** and **asso-
ciated costs**

06



QuiCoax,
the new
**Standard of
Connection**



DATA SHEET

REFERENCE		AA QC 211	AA QC 182
Code		111011	111012
Inputs	N.	1	1
Outputs	N.	1	2
Frequency Range	MHz	47 -694	47 -694
Gain	dB	21	18
Regulation	dB	10	10
Output Level DIN 45004B	dB μ V	114	2 x 110
Return Loss	dB	>10	>10
Noise Figure	dB	<3	<3
Power Supply	V	100-240	100-240
Power Consumption	W	0,9	0,9