



EKSELANS BY ITS



DERIVADORES QuiCoax · DERIVATEURS QuiCoax
DERIVATORI QuiCoax · DISTRIBUIDORES QuiCoax · QuiCoax TAPS
DQCF212 · DQCF216 · DQCF220 · DQCF224

REFERENCIA	RÉFÉRENCE	ARTICOLO	REFERÊNCIA	REFERENCE		DQCF 212	DQCF 216	DQCF 220	DQCF 224
Código	Code	Codice	Código	Code		142034	142035	142036	142037
Banda de paso	Bande passante	Banda passante	Banda de passagem	Passband	MHz	5-2400			
Salidas	Sorties	Uscite	Saídas	Outputs	Nº	2			
Atenuación de derivación	Perte sortie dérivée	Attenuazione di derivazione	Atenuação de derivação	Tap loss	dB (+/-)	12	16	20	24
Pérdidas de paso	Affaiblissement de passage	Perdite di passaggio	Perdas inserção	Insertion loss	dB 47-950 MHz	<2.4	<1.5	<1	<0.7
					dB 950-2150 MHz	<4	<2.1	<1.9	<1.7
Desacoplo entre salidas	Protection entre sorties	Isolamento tra uscite	Isolamento entre as saídas	Isolation between outputs	dB 47-950 MHz	>30	>28	>29	>28
					dB 950-2150 MHz	>20	>28	>22	>24
Perdidas de retorno	Affaiblissement de réflexion	Perdite di ritorno	Perdas de retorno	Return loss	dB 47-950 MHz	>15	>15	>15	>18
					dB 950-2150 MHz	>12	>12	>12	>15
Paso de corriente	Passage de courant	Passaggio DC	Passagem de corrente	DC Pass	mA	500			
Apantallamiento	Blindaje	Schermatura	Blindagem	Shielding		Clase A +10dB			