

POWER SUPPLIES



FA QC 24 · FA QC 242
FA QC 12 · FA QC 122

- ✓ Switched power supplies
- ✓ Ultra-compact size
- ✓ Suitable for 80x80mm junction box
- ✓ Easy to install, just a few seconds
- ✓ QuiCoax connection system
- ✓ Zamak quiCoax case high protection
- ✓ Working led indicator
- ✓ **New generation quiCoax system, even easier connection**



FA QC 242



80x 80 mm junction box
installation

01



Reduce to
minimum
installation time

02



**No need
of tools**

03



Guarantees
an **excellent
connected** and
minimizes the
space

04



Very high
**shielding factor
CLASS A +10dB**
throughout the
band

05



Eliminate the use
of **connectors**
and **associated
costs**

06



**QuiCoax,
the new
Standard of
Connection**



TECHNICAL TABLE

REFERENCE		FA QC 24	FA QC 242	FA QC 12	FA QC 122
Code		053003	053004	053001	053002
Outputs	N°	1	2	1	2
Frequency range	MHz	47-1000	47-1000	47 - 2150	47 - 2150
Insertion loss	dB	<2	<4	<2	<4
Output voltage	Vdc	24	24	12 / 13-18	12
Maximum current output	mA	150	150	300	300
Power supply	Vac	100/240	100/240	100/240	100/240
Dimensions	mm	62 x 60 x 22			