

LTE FILTERS

FE 690 · FE 686

Lte2

- ✓ Low passband insertion loss
- ✓ High LTE band rejection
- ✓ Reversible input / output



FE 690 · FE 686

TECHNICAL TABLE

REFERENCE		FE 690	FE 686
Code		031028	031026
Passband	MHz	5 - 694	5 - 686
Insertion loss	dB 5-678 MHz	<0,8	<1
	dB 686 MHz	<1	<3,5
	dB 690 MHz	<3,5	<12
	dB 694 MHz	<12	>25
	dB 698 MHz	>25	>25
Stop band	MHz	698-862	694-862
DC Pass	mA	300 mA	300 mA