

MICRO LINE AMPLIFIER

MCAL 381 LR



- √ Passive return channel
- √ Class A shielding
- √ Zamak box with heat sink
- √ LED operating light
- √ Compatible with coaxial cable internet distribution Ekoax system



MCAL 381 LR



MCAL 381 LR OPEN

TECHNICAL TABLE

REFERENCE		MCAL 381 LR
Code		061007
Input	N°	1
Frequency	MHz	5-65 / 87-1000
Gain	dB	-2 / 26-32
Regulation	dB	20
Output level DIN 45004B	dBμV	114
Return loss	dB	>10
Noise figure	dB	<4
Power supply	Vac	230 +/-10%
Consumption	W	2,5