

---

## DBS MODULATOR

---

### MD A

- √ Easy output channel programming through display
- √ Full band (47 - 862 MHz)
- √ Multistandard
- √ High output level
- √ L and R audio inputs
- √ TV mix



MD A



CSR



## TECHNICAL TABLE

REFERENCE		MD A
Code		121001
Inputs	N°	2 x AUDIO + VIDEO
Audio regulation	dB	0-14
RF Outputs	N°	1
Frequency Range	MHz	47-862
Standards		B/G/D/K/H/I/L/M/N
Regulation	dB	15
Ouput level	dB $\mu$ V	90
Insertion losses	MHz/ dB	47-862/2 862-2150/4
Mains voltage	Vac	230 +/-10%
Current consumption	W	2,5

CODE	REFERENCE	DESCRIPTION
123001	CSR	SCART / 3 x RCA cable