

MIXER/ DEMIXER RETURN PATH

MI RP GB

GIGAEKOAX

- √ Mezclador / Desmezclador de canal de retorno
- √ **GIGAEKOAX** compatible



MI RP GB

TECHNICAL INFORMATION

REFERENCE		MI RP GB	
Code		132003	
Inputs		DATA	TV
Input connector		F	F
Frequency range	MHz	5-100	120-2150
Insertion loss	dB	<0.5	<1
Rejection	dB	>30	>25
Outputs	N°	1= DATA + TV	
Output connectors		F	
DC Pass		NO	SI